arXiv:1301.5142v1 [cs.CR] 22 Jan 2013

Key Agreement Over A State-Dependent 3-Receiver Broadcast Channel

Mohsen Bahrami, Ali Bereyhi, Sadaf Salehkalaibar, and Mohammad Reza Aref
Information Systems and Security Lab (ISSL),
Sharif University of Technology, Tehran, Iran,
Email: {bahramy, bereyhi, s_saleh}@ee.sharif.edu, aref@sharif.edu

***Abstract*—In this paper, we consider the problem of secret key agreement in state-dependent 3-receiver broadcast channels. In the proposed model, there are two legitimate receivers, an eavesdropper and a transmitter where the channel state information is non-causally available at the transmitter. We consider two setups. In the first setup, the transmitter tries to agree on a common key with the legitimate receivers while keeping it concealed from the eavesdropper. Simultaneously, the transmitter agrees on a private key with each of the legitimate receivers that needs to be kept secret from the other legitimate receiver and the eavesdropper. For this setup, we derive inner and outer bounds on the secret key capacity region. In the second setup, we assume that a backward public channel is available between the receivers and the transmitter. Each legitimate receiver wishes to share a private key with the transmitter. For this setup, an outer bound on the secret key-private capacity is found when the channel state information is non-causally available at the transmitter and is shown to coincide with an inner bound for some special cases. Furthermore, the capacity region of the secret key in the state-dependent wiretap channel can be deduced from our inner and outer bounds.**

I. INTRODUCTION

Secret key sharing is attended in different contexts. Confidential communication, sending private messages and secure dividing between users in a network are some of the problems that dealing with secret key agreement as a bottleneck. In particular, its potential makes a lot of motivations on wireless networking community. In 1949, Shannon introduced a perfect security condition in a system with an eavesdropper. He offered that, for perfect secrecy, the key's randomness must be grater than the message's randomness [1]. He utilized the entropy function to measure the randomness [2]. For key agreement over a network, we need the common randomness between legitimate users. Common randomness can be achieved through correlated sources or channel distribution, which categorizes secret key agreement into two different models, Source model and Channel model. The problem of secret key agreement in the source model was first studied by Ahlswede and Csiszar [3]. They considered a network with two legitimate users and an eavesdropper. The legitimate users are connected with an insecure noiseless channel while observing correlated sources. The legitimate users intend to agree on a secret key for secure communication. In the channel model, using noisy channel may not have sufficient common randomness itself. Maurer used a backward public channel to provide enough common randomness between the legitimate users [4]. In this model, public discussion is used in the wiretap channel. In [5], Gohari and Anantharam studied a multiple terminals channel model where legitimate terminals and an eavesdropper are all connected by a M-receiver broadcast channel and an interactive public channel. Only a set of legitimate terminals have the ability to transmit messages over the public channel. Upon receiving noisy messages from the M-receiver broadcast channel and insecure messages from the public channel, the legitimate terminals agree on a common key. Instead of using the public channel, correlated sources can be utilized in the channel model. The correlation between the sources acts as common randomness and helps the legitimate users to agree on secret keys. Khisti $et.\ al.$, established this idea in a 2-receiver broadcast channel with an eavesdropper [6]. In this model, the transmitter and the legitimate receiver have access to correlated sources and agree on a private key. Salimi and Skoglund, developed the channel model with correlated sources in a generalized multiple access channel where each of transmitters intends to agree on an independent private key with a receiver [7]. Assumption of channel state information accessibility is more practical than the correlated sources existence in the channel model. In such networks, the channel state information can be considered as common randomness for secret key generation. In [8]-[10], the problem of secret key sharing is investigated over the wiretap channel with non-causal and causal channel state information.

In each network, there are different classes of users. Consider a network with four types of users, Trusted Center (TC), Cluster Node (CN), End Node (EN) and illegal user, which have different levels of accessibility. This network can be divided into sub-networks. Each sub-network contains one CN and some ENs. The CNs manage sub-networks while the whole network is controlled by the TC. The TC broadcasts data signals to all users, however, control signals are only transmitted for CNs. In such networks, control signals must be kept secret from the ENs. In addition, the illegal users try to eavesdrop on both data and control signals. Motivated by the above scenario, we study the problem of secret key sharing in state-dependent 3-receiver broadcast channels where Channel State Information (CSI) is non-causally available at the transmitter. We consider four users which are two CNs, a TC and an illegal user. Without loss of generality ENs are not

---

This work was partially supported by Iranian NSF under contract no. $88114/46 - 2010$.

considered. Two different models are discussed:

- *No Public Discussion*: Here, the transmitter intends to agree on a common key with the legitimate receivers and a private key with the corresponding receivers.
- *With Public Discussion*: An insecure public channel is available between the receivers and the transmitter. Each legitimate receiver wishes to agree on a private key with the transmitter.

In the first model, an inner bound to the secret key capacity region is derived when joint source channel coding scheme is used. The coding scheme combines the aspects of both source and channel coding for secret key generation. Also, an outer bound to the secret key capacity region is obtained. In the second model, we establish an inner bound on the secret key capacity region where the double random binning is employed. An explicit outer bound on the secret key capacity region is found and for some special cases, the secret key capacity region is established. Furthermore, it is shown that the capacity region of the secret key in the state-dependent 2-receiver broadcast channel with an eavesdropper can be deduced from our inner and outer bounds.

The rest of the paper is organized as follows. In Section II, the system model is described. In Section III, our main results and the intuitions behind them are given. In Section IV, proofs of the Theorems are presented. Finally, conclusions are provided in Section V.

II. PROBLEM DEFINITION

Throughout the paper, we denote a discrete random variable with an upper case letter (e.g., X) and its realization by the lower case letter (e.g., x). We denote the probability density function of X over $\mathcal{X}$ with $p_X(x)$ and the conditional probability density function of Y given X by $p_{Y|X}(y|x)$. Finally, we use Y^n to indicate vector $(Y_1, Y_2, \dots, Y_n)$.

In order to investigate the problem of secret key agreement over state-dependent 3-receiver broadcast channels, we consider a channel model consisting of a transmitter, two legitimate receivers and an eavesdropper. The transmitter communicates with the other three users over a 3-receiver broadcast channel. We assume that the channel is discrete memoryless with an input alphabet $\mathcal{X}$, output alphabets $\mathcal{Y}_1, \mathcal{Y}_2$ and $\mathcal{Z}$ depending on a parameter S with values in a set $\mathcal{S}$.

In the described model, we consider two cases separately; A. no public discussion is allowed between the transmitter and the receivers. B. public discussion is allowed between the users.

A. The Model Without Public Discussion

In the model without public discussion, as Fig. 1 illustrates, the CSI is available at the transmitter. The transmitter needs to generate three random variables U_0, U_1 and U_2 according to the conditional probability distribution $p_{U_0,U_1,U_2|S}(u_0, u_1, u_2|s)$, which cover S. First, the transmitter generates

$$k_0 = f_0(u_0^n, s^n), k_0 \in [1 : 2^{nR_0}) \tag{1}$$



Fig. 1. The state-dependent 3-reveiver broadcast channel without public discussion

as a common key for sharing with the legitimate receivers, also, computes two independent keys

$$k_1 = f_1(u_0^n, u_1^n, s^n), k_1 \in [1 : 2^{nR_1}) \tag{2}$$

$$k_2 = f_2(u_0^n, u_2^n, s^n), k_2 \in [1 : 2^{nR_2}) \tag{3}$$

as private keys for sharing with the first and second legitimate receivers, respectively. After that, the transmitter determines the channel input x_i to the channel as a deterministic function such that $x_i = x_i(u_{0i}, u_{1i}, u_{2i}, s_i)$ for $i \in [1 : n]$. Consequently, the outputs y_{1i}, y_{2i} and z_i are observed by the receivers. The legitimate receivers intend to estimate the keys according to deterministic functions as follows:
the first legitimate receiver:

$$\hat{k}_{01} = g_{01}(y_1^n, u_0^n) \qquad , \qquad \hat{k}_1 = g_1(y_1^n, u_0^n, u_1^n) \tag{4}$$

the second legitimate receiver:

$$\hat{k}_{02} = g_{02}(y_2^n, u_0^n) \qquad , \qquad \hat{k}_2 = g_2(y_2^n, u_0^n, u_2^n) \tag{5}$$

Definition 1: A rate triple (R_0, R_1, R_2) is said to be achievable if for every $\epsilon > 0$ and sufficiently large n, there exists a protocol such that

$$\Pr\{\cup_{i=1}^2 \{K_0 \neq \hat{K}_{0i}\}\} < \epsilon \tag{6}$$

$$\Pr\{K_1 \neq \hat{K}_1\} < \epsilon \ , \ \Pr\{K_2 \neq \hat{K}_2\} < \epsilon \tag{7}$$

$$\frac{1}{n} I(K_i; Z^n) < \epsilon \qquad \text{for} \quad i = 0, 1, 2 \tag{8}$$

$$\frac{1}{n} I(K_1; K_0, K_2, Y_2^n) < \epsilon \tag{9}$$

$$\frac{1}{n} I(K_2; K_0, K_1, Y_1^n) < \epsilon \tag{10}$$

$$\frac{1}{n} \log \mid K_i \mid < \frac{1}{n} H(K_i) + \epsilon \qquad \text{for} \quad i = 0, 1, 2 \tag{11}$$

$$\frac{1}{n} H(K_i) > R_i - \epsilon \qquad \text{for} \quad i = 0, 1, 2 \tag{12}$$

Equations (6) and (7) are the reliability conditions of the keys. Equation (8) shows that the eavesdropper can not reconstruct the keys. Equations (9) and (10) mean that each legitimate receiver has efficiently no information about the other legitimate receiver's private key. Finally, set of equations (11) and (12) investigate uniformity conditions.

Definition 2: The key capacity region is the set of all achievable rate triples (R_0, R_1, R_2).

In the next sub-section, we define the problem of secret key agreement in state-dependent 3-receiver broadcast channels when a public discussion is allowed between the transmitter and the receivers.

B. The Model With Public Discussion

In the model with public discussion, as Fig. 2 illustrates, the CSI is also known non-causally at the transmitter and a public channel is available from the receivers to the transmitter. This model has some differences with the model discussed in sub-section II. A. In the current model, the legitimate receivers generate secret keys and use the public channel to transmit the required information to the transmitter for the key reconstruction. However, in the model without public channel, the transmitter generates the secret keys and transmits the required information via the 3-receiver broadcast channel to the legitimate receivers. The transmitter sends the ith channel input as a function of CSI, i.e., $x_i = x_i(s^n)$. After receiving y_1^n and y_2^n, the first and second legitimate receivers compute private keys

$$k_1 = f_1(y_1^n), \qquad k_1 \in [1 : 2^{nR_1}) \tag{13}$$
$$k_2 = f_2(y_2^n), \qquad k_2 \in [1 : 2^{nR_2}) \tag{14}$$

respectively. After that, the legitimate receivers transmit ψ_1 and ψ_2 over the public channel as deterministic functions of their observations from the channel ψ_1 and ψ_2. The transmitter computes $\hat{k}_1$ and $\hat{k}_2$ as the estimation of keys k_1 and k_2 such that

$$\hat{k}_1 = g_1(x^n, s^n, \psi_1) \qquad , \qquad \hat{k}_2 = g_2(x^n, s^n, \psi_2). \tag{15}$$

Definition 3: A rate pair (R_1, R_2) is said to be achievable if for every $\epsilon > 0$ and sufficiently large n, there exists a protocol such that

$$\Pr\{K_1 \neq \hat{K}_1\} < \epsilon \ , \ \Pr\{K_2 \neq \hat{K}_2\} < \epsilon \tag{16}$$
$$\frac{1}{n} I(K_1; K_2, Y_2^n, \psi_1, \psi_2) < \epsilon \tag{17}$$
$$\frac{1}{n} I(K_2; K_1, Y_1^n, \psi_1, \psi_2) < \epsilon \tag{18}$$
$$\frac{1}{n} I(K_i; Z^n, \psi_1, \psi_2) < \epsilon \qquad \text{for} \quad i = 1, 2 \tag{19}$$
$$\frac{1}{n} \log \mid K_i \mid < \frac{1}{n} H(K_i) + \epsilon \qquad \text{for} \quad i = 1, 2 \tag{20}$$
$$\frac{1}{n} H(K_i) > R_i - \epsilon \qquad \text{for} \quad i = 1, 2 \tag{21}$$

Equation (16) is the reliability conditions of the private keys. Equations (17), (18) and (19) mean that the eavesdropper and each legitimate receiver have efficiently no information about the other legitimate receiver's private key. Finally, the set of equations (20) and (21) investigate uniformity conditions.

Definition 4: The private key capacity region is the set of all achievable rate pairs (R_1, R_2).



Fig. 2. The state-dependent 3-receiver broadcast channel with presence of public discussion

III. MAIN RESULTS

In this section, we state the main results about the described models. We discuss the cases of no public discussion in sub-section III.A and with public discussion in sub-section III.B.

A. The Model Without Public Discussion

For the model without public discussion, we establish the following inner and outer bounds on the secret key capacity region.

Theorem 1 (Inner Bound): The rate triple (R_0, R_1, R_2) is achievable for the model without public discussion if:

$$\begin{aligned} R_0 &\leq [\min\{I(U_0;Y_1), I(U_0;Y_2)\} - I(U_0;Z)]^+ \\ R_1 &\leq [\min\{I(U_1;Y_1|U_0) - I(U_1;Y_2,U_2|U_0), \\ &\qquad I(U_1;Y_1|U_0) - I(U_1;Z|U_0)\}]^+ \\ R_2 &\leq [\min\{I(U_2;Y_2|U_0) - I(U_2;Y_1,U_1|U_0), \\ &\qquad I(U_2;Y_2|U_0) - I(U_2;Z|U_0)\}]^+ \end{aligned} \tag{22}$$

subject to the constraints:

$$\begin{aligned} I(U_0;Y_1) &\geq I(U_0;S) \\ I(U_0;Y_2) &\geq I(U_0;S) \\ I(U_1;Y_1|U_0) &\geq I(U_1;S|U_0) \\ I(U_2;Y_2|U_0) &\geq I(U_2;S|U_0) \end{aligned} \tag{23}$$

for some input distributions:

$$\begin{aligned} &p_{S,U_0,U_1,U_2,X,Y_1,Y_2,Z}(s,u_0,u_1,u_2,x,y_1,y_2,z) = \\ &p_S(s)p_{U_0|S}(u_0|s)p_{U_1|S,U_0}(u_1|s,u_0)p_{U_2|S,U_0}(u_2|s,u_0) \\ &p_{X|S,U_0,U_1,U_2}(x|s,u_0,u_1,u_2)p_{Y_1,Y_2,Z|X,S}(y_1,y_2,z|x,s) \end{aligned}$$

Proof: See Section IV. A.

Where the function $[x]^+$ equals to x if $x \geq 0$ and 0 if $x < 0$. For the achievability, we use a scheme which utilizes joint source channel coding for two discrete memoryless sources over the broadcast channel and also, the random binning to satisfy secrecy constrains.

Theorem 2 (Outer Bound): For the model without public discussion, any rate triple (R_0, R_1, R_2) must satisfy

$$\begin{aligned} R_0 &\leq \min\{I(X,S;Y_1|Z), I(X,S;Y_2|Z)\} \\ R_1 &\leq \min\{I(X,S;Y_1|Y_2), I(X,S;Y_1|Z)\} \end{aligned}$$

$$R_2 \leq \min\{I(X,S;Y_2|Y_1), I(X,S;Y_2|Z)\} \tag{24}$$

for some input distributions $p_{S,X,Y_1,Y_2,Z}$.

Proof: See Section IV. B.

Remark 1: By setting $U_1 = U_2 = \emptyset$ in Theorem 1 and $Y_1 = Y_2$ in Theorem 1 and Theorem 2, the region reduces to the region of the secret key in the wiretap channel with no public discussion which was investigated in [8] by Khisti *et. al.*

B. The Model With Public Discussion

For the model with public discussion, we establish the following inner and outer bounds on the private key capacity region.

Theorem 3 (Inner Bound): The rate pair (R_1, R_2) is achievable for the model with public discussion if:

$$\begin{aligned} R_1 \leq [\min\{&I(X,S;Y_1) - I(Y_1;Y_2), \\ &I(X,S;Y_1) - I(Y_1;Z)\}]^+ \\ R_2 \leq [\min\{&I(X,S;Y_2) - I(Y_1;Y_2), \\ &I(X,S;Y_2) - I(Y_2;Z)\}]^+ \end{aligned} \tag{25}$$

for some input distributions:

$$\begin{aligned} &p_{S,X,Y_1,Y_2,Z}(s,x,y_1,y_2,z) = p_S(s)p_{X|S}(x|s) \\ &p_{Y_1,Y_2,Z|X,S}(y_1,y_2,z|x,s). \end{aligned}$$

Proof: See Section IV. C.

The main idea for achieving the inner bound comes from the Slepian and Wolf coding scheme for distributed lossless source coding problems [11]. In addition, we use the double random binning to satisfy the secrecy constrains.

Remark 2: By setting $Y_1 = Y_2$ in Theorem 3, the inner bound reduces to the inner bound on the secret key in the wiretap channel with public discussion which was studied in [9] by Khisti *et. al.*

Theorem 4 (Outer Bound): For the model with public discussion, any rate pair (R_1, R_2) must satisfy

$$\begin{aligned} R_1 &\leq \min\{I(X,S;Y_1|Y_2), I(X,S;Y_1|Z)\} \\ R_2 &\leq \min\{I(X,S;Y_2|Y_1), I(X,S;Y_2|Z)\} \end{aligned} \tag{26}$$

for some input distributions $p_{S,X,Y_1,Y_2,Z}$.

Proof: The proof follows similar to Theorem 1 in [3].

In the following, we obtain the private key capacity region for some special cases.

Corollary 1: If the input and outputs of a state-dependent 3-receiver broadcast channel form a Markov chain as $Y_1 \to (X,S) \to Z \to Y_2$, i.e., Y_2 and Z are degraded versions of Y_1. The private key capacity region reduces to:

$$R_1 = I(X,S;Y_1|Z) \quad , \quad R_2 = 0 \tag{27}$$

Proof: The achievability follows from Theorem 3 where we have:

$$\begin{aligned} R_1 &\geq I(X,S;Y_1) - \max\{I(Y_1;Y_2), I(Y_1,Z)\} \\ &\overset{(a)}{=} I(X,S;Y_1) - I(Y_1;Z) \\ &= I(X,S,Z;Y_1) - I(Z;Y_1|X,S) - I(Y_1;Z) \\ &\overset{(b)}{=} I(Y_1;Z) + I(X,S;Y_1|Z) - I(Y_1;Z) = I(X,S;Y_1|Z) \end{aligned}$$

(a) and (b) can be deduced from the Markov chain $Y_1 \to (X,S) \to Z \to Y_2$. According to Theorem 4, the proof of converse is established.

Corollary 2: If the input and outputs of a state-dependent 3-receiver broadcast channel form a Markov chain as $Y_1 \to (X,S) \to Y_2 \to Z$, i.e., Y_2 and Z are degraded versions of Y_1. The private key capacity region reduces to:

$$R_1 = I(X,S;Y_1|Y_2) \quad , \quad R_2 = 0 \tag{28}$$

Proof: The proof is similar to Corollary 1.

Corollary 3: If the input and outputs of a state-dependent 3-receiver broadcast channel form a Markov chain as $Y_2 \to (X,S) \to Z \to Y_1$, i.e., Y_1 and Z are degraded versions of Y_2. The private key capacity region reduces to:

$$R_1 = 0 \quad , \quad R_2 = I(X,S;Y_2|Z) \tag{29}$$

Proof: The proof is similar to Corollary 1.

Corollary 4: If the input and outputs of a state-dependent 3-receiver broadcast channel form a Markov chain as $Y_2 \to (X,S) \to Y_1 \to Z$, i.e., Y_1 and Z are degraded versions of Y_2. The private key capacity region reduces to:

$$R_1 = 0 \quad , \quad R_2 = I(X,S;Y_2|Y_1) \tag{30}$$

Proof: The proof is similar to Corollary 1.

IV. PROOFS

In this section, we present the proofs of the main results. This section contains two parts. In the first part, the proofs of the inner and outer bounds on the secret key capacity region for the model without public discussion are given. In the achievability, the hybrid joint source channel coding and the random binning are used. In the second part, the proofs of the model with public discussion are illustrated. The double random binning is utilized to achieve the inner bound. The proofs of the outer bounds are similar to [3] for both cases.

A. Proof of Theorem 1

Fix conditional probability density function

$$p_{U_0,U_1,U_2|S}(u_0,u_1,u_2|s).$$

Codebook Generation: Generate $2^{n\tilde{R}_0}$ sequences $U_0^n(m_{u_0})$ $m_{u_0} \in [1 : 2^{n\tilde{R}_0})$, each according to $\prod_{i=1}^n p_{U_0}(u_{0i})$. Then, randomly and independently partition them into 2^{nR_0} bins. For each m_{u_0}, we generate $2^{n\tilde{R}_1}$ sequences $U_1^n(m_{u_1}),\ \ m_{u_1} \in [1 : 2^{n\tilde{R}_1})$ each according to $\prod_{i=1}^n p_{U_1|U_0}(u_{1i}|u_{0i})$, and partition them into 2^{nR_1} bins. Similarly, for each m_{u_0}, we generate $2^{n\tilde{R}_2}$ sequences $U_2^n(m_{u_2}),\ \ m_{u_2} \in [1 : 2^{n\tilde{R}_2})$ each according to $\prod_{i=1}^n p_{U_2|U_0}(u_{2i}|u_{0i})$. At the end, randomly partition the sequences U_2^n into 2^{nR_2} bins. Codebook $\mathcal{C}^{U_i}$ contains $2^{n\tilde{R}_i}$ sequences U_i^n for $i = 0, 1, 2$.

Encoding: For each sequence s^n, the encoder chooses a triple $(m_{u_0}, m_{u_1}, m_{u_2})$ such that

$$(s^n, u_0^n(m_{u_0}), u_1^n(m_{u_1}), u_2^n(m_{u_2})) \in \mathcal{T}_\epsilon^{(n)}(S, U_0, U_1, U_2).$$

Then, the transmitter sends $x_i = x_i(s_i, u_{0i}, u_{1i}, u_{2i})$ for $i \in [1:n]$ over the 3-receiver broadcast channel. By the covering lemma [12], this can be done with an arbitrarily small probability of error if:

$$\begin{aligned}\tilde{R}_0 &\geq I(U_0; S)\\ \tilde{R}_1 &\geq I(U_1; S|U_0)\\ \tilde{R}_2 &\geq I(U_2; S|U_0)\end{aligned} \tag{31}$$

Decoding: After receiving y_1^n, the first legitimate receiver finds a sequence pair $(u_0^n(\hat{m}_{u_0}), u_1^n(\hat{m}_{u_1}))$, such that

$$(u_0^n(\hat{m}_{u_0}), u_1^n(\hat{m}_{u_1}), y_1^n) \in \mathcal{T}_\epsilon^{(n)}(U_0, U_1, Y_1).$$

Similarly, upon observing y_2^n the second legitimate receiver finds a sequence pair $(u_0^n(\hat{m}_{u_0}), u_2^n(\hat{m}_{u_2}))$, such that

$$(u_0^n(\hat{m}_{u_0}), u_2^n(\hat{m}_{u_2}), y_2^n) \in \mathcal{T}_\epsilon^{(n)}(U_0, U_2, Y_2).$$

By the packing lemma [12], the probability of error tends to zero as $n \to \infty$ if:

$$\begin{aligned}\tilde{R}_0 &\leq \min\{I(U_0; Y_1), I(U_0; Y_2)\}\\ \tilde{R}_1 &\leq I(U_1; Y_1|U_0)\\ \tilde{R}_2 &\leq I(U_2; Y_2|U_0).\end{aligned} \tag{32}$$

Secret Key Generation: After decoding, the transmitter and the legitimate receivers agree on the bin index of u_0^n to be the public key k_0. The transmitter and the first legitimate receiver agree on the bin index of u_1^n as the private key, likewise, the second legitimate receiver agrees on the bin index of u_2^n as the private-key k_2 with the transmitter.

Analysis of Secrecy: In order to check the security condition on the common key rate averaged over the random codebook assignments $\mathcal{C}^{U_0}$, we have:

$$\begin{aligned}&I(K_0; Z^n|\mathcal{C}^{U_0}) = H(K_0|\mathcal{C}^{U_0}) - H(K_0|Z^n, \mathcal{C}^{U_0})\\ &= H(K_0|\mathcal{C}^{U_0}) - H(K_0, U_0^n|Z^n, \mathcal{C}^{U_0}) + H(U_0^n|K_0, Z^n, \mathcal{C}^{U_0})\\ &= H(K_0|\mathcal{C}^{U_0}) - H(U_0^n|Z^n, \mathcal{C}^{U_0}) - H(K_0|U_0^n, Z^n, \mathcal{C}^{U_0})\\ &+ H(U_0^n|K_0, Z^n, \mathcal{C}^{U_0}) \overset{(a)}{=} H(K_0|\mathcal{C}^{U_0}) - H(U_0^n|Z^n, \mathcal{C}^{U_0})\\ &+ H(U_0^n|K_0, Z^n, \mathcal{C}^{U_0}) \overset{(b)}{\leq} nR_0 - H(U_0^n|Z^n, \mathcal{C}^{U_0})\\ &+ H(U_0^n|K_0, Z^n, \mathcal{C}^{U_0}) \leq nR_0 - n\tilde{R}_0 + nI(U_0; Z) + n\tilde{R}_0 - nR_0\\ &- nI(U_0; Z) + n\epsilon = n\epsilon\end{aligned}$$

as K_0 is the bin index of U_0^n, the equality $H(K_0|U_0^n, Z^n, \mathcal{C}^{U_0}) = 0$ holds which deduces (a). (b) can be deduced from inequalities $H(U_0^n|Z^n, \mathcal{C}^{U_0}) \leq n\tilde{R}_0 - nI(U_0; Z) + n\epsilon$ and $H(U_0^n|K_0, Z^n, \mathcal{C}^{U_0}) \leq n\tilde{R}_0 - nR_0 - nI(U_0; Z) + n\epsilon$ if $R_0 \leq \min\{I(U_0; Y_1), I(U_0; Y_2)\} - I(U_0; Z) + \epsilon$, the proof is similar to [Lemma 22.3, 12].

Also, to check the secrecy conditions for the private key rate R_1 averaged on the random codebook assignments $\mathcal{C}^{U_1}$, we have:

$$\begin{aligned}&I(K_1; K_0, K_2, Y_2^n|\mathcal{C}^{U_1}) \leq I(K_1; U_0^n, U_2^n, Y_2^n|\mathcal{C}^{U_1})\\ &= H(K_1|\mathcal{C}^{U_1}) - H(K_1|U_0^n, U_2^n, Y_2^n|\mathcal{C}^{U_1})\\ &= H(K_1|\mathcal{C}^{U_1}) - H(K_1, U_1^n|U_0^n, U_2^n, Y_2^n, \mathcal{C}^{U_1})\\ &+ H(U_1^n|K_1, U_0^n, U_2^n, Y_2^n, \mathcal{C}^{U_1})\\ &= H(K_1|\mathcal{C}^{U_1}) - H(U_1^n|U_0^n, U_2^n, Y_2^n, \mathcal{C}^{U_1})\\ &- H(K_1|U_0^n, U_1^n, U_2^n, Y_2^n, \mathcal{C}^{U_1}) + H(U_1^n|K_1, U_0^n, U_2^n, Y_2^n, \mathcal{C}^{U_1})\\ &\overset{(a)}{=} H(K_1|\mathcal{C}^{U_1}) - H(U_1^n|U_0^n, U_2^n, Y_2^n, \mathcal{C}^{U_1})\\ &+ H(U_1^n|K_1, U_0^n, U_2^n, Y_2^n, \mathcal{C}^{U_1}) \overset{(b)}{\leq} nR_1 - n\tilde{R}_1 + nI(U_1; U_2, Y_2|U_0)\\ &+ n\tilde{R}_1 - nR_1 - nI(U_1; U_2, Y_2|U_0) + n\epsilon = n\epsilon\end{aligned}$$

as K_1 is the bin index of U_1^n, the equality $H(K_1|U_0^n, U_1^n, U_2^n, Y_2^n, \mathcal{C}^{U_1}) = 0$ holds which deduces (a). (b) can be deduced from inequalities $H(U_1^n|U_0^n, U_2^n, Y_2^n, \mathcal{C}^{U_1}) \leq n\tilde{R}_1 - nI(U_1; Y_2, U_2|U_0) + n\epsilon$ and $H(U_1^n|K_1, U_0^n, U_2^n, Y_2^n, \mathcal{C}^{U_1}) \leq n\tilde{R}_1 - nR_1 - nI(U_1; Y_2, U_2|U_0) + n\epsilon$ if $R_1 \leq I(U_1; Y_1|U_0) - I(U_1; Y_2, U_2|U_0) + n\epsilon$, the proof is similar to [Lemma 22.3, 12]. And,

$$\begin{aligned}&I(K_1; Z^n|\mathcal{C}^{U_1}) \leq I(K_1; U_0^n, Z^n|\mathcal{C}^{U_1})\\ &= H(K_1|\mathcal{C}^{U_1}) - H(K_1|U_0^n, Z^n, \mathcal{C}^{U_1}) = H(K_1|\mathcal{C}^{U_1})\\ &- H(K_1, U_1^n|U_0^n, Z^n, \mathcal{C}^{U_1}) + H(U_1^n|K_1, U_1^n, Z^n, \mathcal{C}^{U_1})\\ &= H(K_1|\mathcal{C}^{U_1}) - H(U_1^n|U_0^n, Z^n, \mathcal{C}^{U_1}) - H(K_1|U_0^n, U_1^n, Z^n, \mathcal{C}^{U_1})\\ &+ H(U_1^n|K_1, U_0^n, Z^n, \mathcal{C}^{U_1}) \overset{(a)}{=} H(K_1|\mathcal{C}^{U_1}) - H(U_1^n|U_0^n, Z^n, \mathcal{C}^{U_1})\\ &+ H(U_1^n|K_1, U_0^n, Z^n, \mathcal{C}^{U_1}) \overset{(b)}{\leq} nR_1 - n\tilde{R}_1 + nI(U_1; Z|U_0) + n\tilde{R}_1\\ &- nR_1 - nI(U_1; Z|U_0) + n\epsilon = n\epsilon\end{aligned}$$

as K_1 is the bin index of U_1^n, the equality $H(K_1|U_0^n, U_1^n, Z^n, \mathcal{C}^{U_1}) = 0$ holds which deduces (a). (b) can be deduced from inequalities $H(U_1^n|U_0^n, Z^n, \mathcal{C}^{U_1}) \leq n\tilde{R}_1 - nI(U_1; Z|U_0) + n\epsilon$ and $H(U_1^n|K_1, U_0^n, Z^n, \mathcal{C}^{U_1}) \leq n\tilde{R}_1 - nR_1 - nI(U_1; Z|U_0) + n\epsilon$ if $R_1 \leq I(U_1; Y_1|U_0) - I(U_1; Z|U_0) + n\epsilon$, the proof is similar to [Lemma 22.3, 12]. Finally, we have:

$$\begin{aligned}R_1 \leq \min\{&I(U_1; Y_1|U_0) - I(U_1; Y_2, U_2|U_0),\\ &I(U_1; Y_1|U_0) - I(U_1; Z|U_0)\}.\end{aligned}$$

Similarly, we can check the security conditions for K_2.

B. Proof of Theorem 2

In our described model, each legitimate receiver should be able to estimate common key k_0 correctly and according to the Fano's inequality $\frac{1}{n}H(K_0|Y_1^n) \leq \epsilon$ and $\frac{1}{n}H(K_0|Y_2^n) \leq \epsilon$. and also, the security condition $\frac{1}{n}I(K_0; Z^n) \leq \epsilon$ must be satisfied: We find an outer bound on R_0. (outer bounds on R_1 and R_2 can be obtained similarly)

$$\begin{aligned}&nR_0 = H(K_0) = I(K_0; Y_1^n) + H(K_0|Y_1^n)\\ &\overset{(a)}{\leq} I(K_0; Y_1^n) + n\epsilon \leq I(K_0; Y_1^n, Z^n) + n\epsilon\\ &= I(K_0; Z^n) + I(K_0; Y_1^n|Z^n) + n\epsilon \overset{(b)}{\leq} I(K_0; Y_1^n|Z^n) + 2n\epsilon\\ &\leq I(K_0, K_1, K_2, X^n, S^n; Y_1^n|Z^n) + 2n\epsilon = I(X^n, S^n; Y_1^n|Z^n)\\ &+ I(K_0, K_1, K_2; Y_1^n|Z^n, X^n, S^n) + 2n\epsilon\\ &\overset{(c)}{\leq} I(X^n, S^n; Y_1^n|Z^n) + 3n\epsilon\\ &\leq \sum_{i=1}^{n} I(X_i, S_i; Y_{1i}|Z_i) + 3n\epsilon \overset{(d)}{\leq} I(X_Q, S_Q; Y_{1Q}|Z_Q, Q) + 3n\epsilon\\ &= I(X_Q, S_Q; Y_{1Q}|Z_Q) + 3n\epsilon\end{aligned}$$

where (a) follows from the Fano's inequality, (b) comes from the security condition, (c) can be deduced from the

Markov chain $(K_0, K_1, K_2) \rightarrow (S^n, X^n) \rightarrow (Y_1^n, Y_2^n, Z^n)$ and (d) can be obtained by defining Q as a uniform random variable over $[1:n]$. Also in a similar way, we have $R_0 \leq I(X, S; Y_2|Z)$. Finally, we have

$$R_0 \leq \min\{I(X, S; Y_1|Z), I(X, S; Y_2|Z)\}.$$

C. Proof of Theorem 3

Our achievability proof is closely related to the achievability proof in [9]. In addition, the double random binning is used to satisfy secrecy constrains. The achievability proof is as follows:

Codebook Generation: We consider the set of all typical sequences y_1^n and y_2^n. The number of the typical sequences y_1^n and y_2^n are $2^{n(H(Y_1)+\epsilon_1)}$ and $2^{n(H(Y_2)+\epsilon_2)}$, respectively, where $\epsilon_1, \epsilon_2 > 0$ can be chosen arbitrarily small. We utilized the double random binning. Therefore, we have:

$$\begin{aligned} & y_j^n(i_j, i_j', i_j'') \qquad \text{for } j = 1, 2 \\ & i_j \in [1 : 2^{nH(Y_j)}),\ i_j' \in [1 : 2^{nR_j'}),\ i_j'' \in [1 : 2^{nR_j''}) \end{aligned}$$

Encoding: With the channel state sequence s^n observed, the transmitter randomly and independently generates a codeword x^n according to the conditional distribution $\prod_{i=1}^{n} p_{X|S}(x_i|s_i)$, and transmits x_i for $i \in [1:n]$ over the 3-receiver broadcast channel with the channel probability distribution $p_{Y_1,Y_2,Z|X,S}$.

Use of The Public Channel: On the basis of channel output sequence y_1^n the first legitimate receiver finds the bin index of y_1^n according to the codebook and sends the bin index of y_1^n via the public channel. Similarly, the second legitimate receiver finds the bin index of y_2^n and transmits the bin index of y_2^n over the public channel.

Secret Key Generation: The transmitter upon receiving the bin indices of y_1^n and y_2^n from the public channel and by the knowledge of x^n and s^n can recover y_1^n and y_2^n. Then both transmitter and the first legitimate receiver agree on the sub-bin index of y_1^n as the private key. Similarly, the second legitimate receiver and the transmitter agree on the sub-bin index of y_2^n as their private key.

Analysis of The Probability of Error: From the Slepian and Wolf coding, the transmitter finds y_1^n and y_2^n after receiving the bin indices of y_1^n and y_2^n from the public channel, respectively. By the packing lemma, the probability of error tends to zero as $n \rightarrow \infty$ if:

$$\begin{aligned} H(Y_1) - R_1' &\leq I(X, S; Y_1) \\ H(Y_2) - R_2' &\leq I(X, S; Y_2) \end{aligned} \tag{33}$$

Analysis of Secrecy: In order to check the security conditions, we have:

$$\begin{aligned} & I(K_1; K_2, Y_2^n, \psi_1, \psi_2) = H(K_1) - H(K_1|K_2, Y_2^n, \psi_1, \psi_2) \\ & = H(K_1) - H(K_1, Y_1^n|K_2, Y_2^n, \psi_1, \psi_2) \\ & + H(Y_1^n|K_1, K_2, Y_2^n, \psi_1, \psi_2) \\ & \overset{(a)}{=} H(K_1) - H(Y_1^n|K_2, Y_2^n \psi_1, \psi_2) + H(Y_1^n|K_1, K_2, Y_2^n, \psi_1, \psi_2) \end{aligned}$$

$$\begin{aligned} & \overset{(b)}{\leq} nR_1'' - nH(Y_1) + nR_1' + nI(Y_1; Y_2) + nH(Y_1) \\ & - nR_1' - nR_1'' - nI(Y_1; Y_2) = n\epsilon \end{aligned}$$

as K_1 is the sub-bin index of Y_1^n, the equality $H(K_1|K_2, Y_1^n, Y_2^n, \psi_1, \psi_2) = 0$ holds which deduces (a). (b) can be deduced from inequalities $H(Y_1^n|K_2, Y_2^n \psi_1, \psi_2) \leq nH(Y_1) - nR_1' - nI(Y_1; Y_2) + n\epsilon$ and $H(Y_1^n|K_1, K_2, Y_2^n, \psi_1, \psi_2) \leq nH(Y_1) - nR_1' - nR_1'' - nI(Y_1; Y_2) + n\epsilon$ if $R_1 \leq I(X, S; Y_1) - I(Y_1; Y_2) + n\epsilon$, the proof is similar to [lemma 22.3, 12].Also in a similar way, we have $R_1 \leq I(X, S; Y_1) - I(Y_1; Z)$. Finally, we have:

$$R_1 \leq min\{I(X, S; Y_1) - I(Y_1; Y_2), I(X, S; Y_1) - I(Y_1; Z)\}.$$

Similarly, we can check the security conditions for K_2.

V. CONCLUSIONS

The problem of secret key agreement over state-dependent 3-receiver broadcast channels is investigated. We study two cases for this problem. In the first case, the transmitter intends to share a common key with both legitimate receivers while keeping it concealed from the eavesdropper. The transmitter wishes to share a private key with each of the legitimate receivers. For this case, we have obtained inner and outer bounds to the secret keys capacity. In the second case, each of the legitimate receivers wants to share a private key with the transmitter using a 3-receiver broadcast channel and a backward public channel. For this case, the private key capacity region are derived for some special cases.

REFERENCES

[1] C. E. Shannon, " Communication theory of secrecy systems," *Bell System Technical Journal*, vol. 28, pp. 656-715, 1949.

[2] C. E. Shannon, "A mathematical theory of communication," *Bell System Technical Journal*, vol. 27, pp. 379-423 and 623-656, 1948.

[3] R. Ahlswede and I. Csiszar, "Common randomness in information theory and cryptography - Part I: Secret sharing, *IEEE Trans. Inf. Theory*, vol. 39, no. 4, pp. 1121-1132, Jul. 1993.

[4] U. M. Maurer, "Secret key agreement by public discussion from common information," *IEEE Trans. Inf. Theory*, vol. 39, no. 3, pp. 733-742, May 1993.

[5] A. A. Gohari and V. Anantharam, "Information-theoretic key agreement of multiple Terminals - Part II: Channel model," *IEEE Trans. Inf. Theory*, vol. 56, no. 8, pp. 3997-4010, Aug. 2010.

[6] A. Khisti, S. Diggavi, and G. Wornell, "Secret-key generation using correlated sources and channels," *IEEE Trans. Inf. Theory*, vol. 58, no. 2, pp. 652-670, Feb. 2012.

[7] S. Salimi and M. Skoglund, "Secret key agreement using correlated sources over the generalized multiple access channel," *Arxiv preprint*, arXiv: 1204.2922v1, Apr. 2012.

[8] A. Khisti, S. Diggavi, and G. Wornell, "Secret key agreement with channel state information at the transmitter," *IEEE Trans. on Information Forensics and Security*, vol. 6, no. 3, pp. 672-681, Sep. 2011.

[9] A. Khisti, "Secret key agreement on wiretap channel with transmitter side information," in *Proc. European Wireless (EW)*, Lucca, Italy, pp. 802-809, Apr. 2010.

[10] A. Khisti, S. Diggavi, and G. Wornell, "Secret key agreement using asymmetry in channel state knowledge," in *Proc. Int. Symp. Inf. Theory*, Seoul, Korea, pp. 2286-2290, Jun.-Jul. 2009.

[11] D. Slepian and J. K. Wolf, "Noiseless coding of correlated information sources," *IEEE Trans. Inf. Theory*, vol. 19, no. 4, pp. 471-480, Jul. 1973.

[12] A. El Gamal and Y. H. Kim, *Network Information Theory*, 1st ed. Cambridge University Press, 2011.